

§ 73.239

§ 73.239 Use of common antenna site.

No FM broadcast station license or renewal of FM broadcast station license will be granted to any person who owns, leases, or controls a particular site which is peculiarly suitable for FM broadcasting in a particular area and (a) which is not available for use by other FM broadcast station licensees; and (b) no other comparable site is available in the area; and (c) where the exclusive use of such site by the applicant or licensee would unduly limit the number of FM broadcast stations that can be authorized in a particular area or would unduly restrict competition among FM broadcast stations.

[28 FR 13623, Dec. 14, 1963]

§ 73.258 Indicating instruments.

(a) Each FM broadcast station shall be equipped with indicating instruments which conform with the specifications described in § 73.1215 for determining power by the indirect method; for indicating the relative amplitude of the transmission line radio frequency current, voltage, or power; and with such other instruments as are necessary for the proper adjustment, operation, and maintenance of the transmitting system.

(b) The function of each instrument shall be clearly and permanently shown in the instrument itself or on the panel immediately adjacent thereto.

(c) In the event that any one of these indicating instruments becomes defective when no substitute which conforms with the required specifications is available, the station may be operated without the defective instrument pending its repair or replacement for a period not in excess of 60 days without further authority of the FCC: *Provided that*, if the defective instrument is the transmission line meter of a station which determines the output power by the direct method, the operating power shall be determined by the indirect method in accordance with § 73.267(c) during the entire time the station is operated without the transmission line meter.

(d) If conditions beyond the control of the licensee prevent the restoration

47 CFR Ch. I (10–1–13 Edition)

of the meter to service within the above allowed period, an informal letter request in accordance with § 73.3549 may be filed with the FCC, Attention: Audio Division, Media Bureau, in Washington, DC for such additional time as may be required to complete repairs of the defective instrument.

[41 FR 36818, Sept. 1, 1976, as amended at 48 FR 44805, Sept. 30, 1983; 50 FR 32416, Aug. 12, 1985; 63 FR 33876, June 22, 1998; 67 FR 13231, Mar. 21, 2002]

§ 73.267 Determining operating power.

(a) The operating power of each FM station is to be determined by either the direct or indirect method.

(b) Direct method. The direct method of power determination for an FM station uses the indications of a calibrated transmission line meter (responsive to relative voltage, current, or power) located at the RF output terminals of the transmitter. This meter must be calibrated whenever there is any indication that the calibration is inaccurate or whenever any component of the metering circuit is repaired or replaced. The calibration must cover, as a minimum, the range from 90% to 105% of authorized power. The meter calibration may be checked by measuring the power at the transmitter terminals while either:

(1) Operating the transmitter into the transmitting antenna, and determining actual operating power by the indirect method described in § 73.267(c); or

(2) Operating the transmitter into a load (of substantially zero reactance and a resistance equal to the transmission line characteristic impedance) and using an electrical device (within ±5% accuracy) or temperature and coolant flow indicator (within ±4% accuracy) to determine the power.

(3) The calibration must cover, as a minimum, the range from 90% to 105% of authorized power and the meter must provide clear indications which will permit maintaining the operating power within the prescribed tolerance or the meter shall be calibrated to read directly in power units.

(c) *Indirect method.* The operating power is determined by the indirect method by applying an appropriate factor to the input power to the last