

The mobile channels may also be assigned for use by base or fixed transmitters under certain circumstances (see §22.567(h)). Unless otherwise indicated, all channels have a bandwidth of 20 kHz and are designated by their center frequencies in MegaHertz.

Base	Mobile	Base	Mobile
VHF Channels			
152.03	158.49	152.57	157.83
152.06	158.52	152.60	157.86
152.09	158.55	152.63	157.89
152.12	158.58	152.66	157.92
152.15	158.61	152.69	157.95
152.18	158.64	152.72	157.98
152.21	158.67	152.75	158.01
152.51	157.77	152.78	158.04
152.54	157.80	152.81	158.07

UHF Channels			
454.025	459.025	454.350	459.350
454.050	459.050	454.375	459.375
454.075	459.075	454.400	459.400
454.100	459.100	454.425	459.425
454.125	459.125	454.450	459.450
454.150	459.150	454.475	459.475
454.175	459.175	454.500	459.500
454.200	459.200	454.525	459.525
454.225	459.225	454.550	459.550
454.250	459.250	454.575	459.575
454.275	459.275	454.600	459.600
454.300	459.300	454.625	459.625
454.325	459.325	454.650	459.650

[59 FR 59507, Nov. 17, 1994; 60 FR 9889, Feb. 22, 1995, as amended at 62 FR 11636, Mar. 12, 1997]

§ 22.565 Transmitting power limits.

The transmitting power of base, mobile and fixed transmitters operating on the channels listed in §22.561 must not exceed the limits in this section.

(a) *Maximum ERP.* The effective radiated power (ERP) of base and fixed transmitters must not exceed the applicable limits in this paragraph under any circumstances.

Frequency range (MHz)	Maximum ERP (watts)
152–153	1400
157–159	150
454–455	3500
459–460	150

(b) *Basic power limit.* Except as provided in paragraph (d) of this section, the ERP of base transmitters must not exceed 500 Watts.

(c) *Height-power limits.* Except as provided in paragraph (d) of this section, the ERP of base transmitters must not exceed the amount that would result in an average distance to the service contour of 41.6 kilometers (26 miles) for VHF channels or 30.7 kilometers (19 miles) for UHF channels. The average distance to the service contour is calculated by taking the arithmetic mean of the distances determined using the procedures specified in §22.567 for the eight cardinal radial directions, excluding cardinal radial directions for which 90% or more of the distance so calculated is over water.

(d) *Encompassed interfering contour areas.* Base transmitters are exempt from the basic power and height-power limits of this section if the area within their interfering contours is totally encompassed by the interfering contours of operating co-channel based transmitters controlled by the same licensee. For the purpose of this paragraph, operating transmitters are authorized transmitters that are providing service to subscribers.

(e) *Adjacent channel protection.* The ERP of base and fixed transmitters must not exceed 500 Watts if they transmit on channel 454.025 MHz and are located less than 7 kilometers (4.3 miles) from any Private Radio Services station receiving on adjacent channel 454.0000 MHz.

(f) *Mobile transmitters.* The transmitter output power of mobile transmitters must not exceed 60 watts.

[59 FR 59507, Nov. 17, 1994, as amended at 70 FR 19309, Apr. 13, 2005]

§ 22.567 Technical channel assignment criteria.

The rules in this section establish technical assignment criteria for the channels listed in §22.561. The criteria in paragraphs (a) through (f) of this section permit channel assignments to be made in a manner such that reception by public mobile receivers of signals from base transmitters, within the service area of such base transmitters, is protected from interference caused by the operation of independent co-channel base and fixed transmitters in the Paging and Radiotelephone Service and central office stations, including

Basic Exchange Telephone Radio Systems (BETRS), in the Rural Radiotelephone Service. Additional criteria in paragraph (g) of this section permit channel assignments to be made in a manner such that BETRS communications are protected from interference caused by the operation of independent co-channel base and fixed transmitters in the Paging and Radiotelephone Service and other central office stations in the Rural Radiotelephone Service. Separate criteria in paragraph (h) of this section apply only to assignment of the channels designated in § 22.561 as mobile channels to base and fixed transmitters, and permit these channel assignments to be made in a manner such that reception by public base and fixed receivers of signals from associated mobile and fixed transmitters is protected from interference caused by the operation of independent co-channel base and fixed transmitters.

(a) *Contour overlap.* The FCC may grant an application requesting assignment of a channel to a proposed base, fixed or central office station transmitter only if:

(1) The interfering contour of the proposed transmitter does not overlap the service contour of any protected co-channel transmitter controlled by a carrier other than the applicant, unless that carrier has agreed in writing to accept any interference that may result from operation of the proposed transmitter; and

(2) The service contour of the proposed transmitter does not overlap the interfering contour of any protected co-channel transmitter controlled by a carrier other than the applicant, unless the application contains a statement that the applicant agrees to accept any interference that may result from operation of the protected co-channel transmitter; and

(3) The area and/or population to which service would be provided by the proposed transmitter is substantial, and service gained would exceed that lost as a result of agreements to accept interference.

(b) *Protected transmitter.* For the purposes of this section, protected transmitters are authorized transmitters for which there is a current FCC public record and transmitters proposed in

prior-filed pending applications, in the Paging and Radiotelephone Service and the Rural Radiotelephone Service.

(c) *VHF service contour.* For base stations transmitting on the VHF channels, the radial distance from the transmitting antenna to the service contour along each cardinal radial is calculated as follows:

$$d = 1.609 \times h^{0.40} \times p^{0.20}$$

where:

d is the radial distance in kilometers

h is the radial antenna HAAT in meters

p is the radial ERP in Watts

(1) Whenever the actual HAAT is less than 30 meters (98 feet), 30 must be used as the value for h in the above formula.

(2) The value used for p in the above formula must not be less than 27 dB less than the maximum ERP in any direction, or 0.1 Watt, whichever is more.

(3) The distance from the transmitting antenna to the service contour along any radial other than the eight cardinal radials is routinely calculated by linear interpolation of distance as a function of angle. However, in resolving petitions to deny, the FCC may calculate the distance to the service contour using the formula in paragraph (c) of this section with actual HAAT and ERP data for the inter-station radial and additional radials above and below the inter-station radial at 2.5° intervals.

(d) *VHF interfering contour.* For base and fixed stations transmitting on the VHF channels, the radial distance from the transmitting antenna to the interfering contour along each cardinal radial is calculated as follows:

(1) If the radial antenna HAAT is less than 150 meters:

$$d = 8.577 \times h^{0.24} \times p^{0.19}$$

where:

d is the radial distance in kilometers

h is the radial antenna HAAT in meters

p is the radial ERP in Watts

Whenever the actual HAAT is less than 30 meters (98 feet), 30 must be used as the value for h in the above formula.

(2) If the radial antenna HAAT is 150 meters or more:

$$d = 12.306 \times h^{0.23} \times p^{0.14}$$

where:

d is the radial distance in kilometers
h is the radial antenna HAAT in meters
p is the radial ERP in Watts

(3) The value used for p in the above formulas must not be less than 27 dB less than the maximum ERP in any direction, or 0.1 Watt, whichever is more.

(4) The distance from the transmitting antenna to the interfering contour along any radial other than the eight cardinal radials is routinely calculated by linear interpolation of distance as a function of angle. However, in resolving petitions to deny, the FCC may calculate the distance to the interfering contour using the appropriate formula in paragraph (d) of this section with actual HAAT and ERP data for the inter-station radial and additional radials above and below the inter-station radial at 2.5° intervals.

(e) *UHF service contour.* For base stations transmitting on the UHF channels, the radial distance from the transmitting antenna to the service contour along each cardinal radial is calculated as follows:

$$d = 1.726 \times h^{0.35} \times p^{0.18}$$

where:

d is the radial distance in kilometers
h is the radial antenna HAAT in meters
p is the radial ERP in Watts

(1) Whenever the actual HAAT is less than 30 meters (98 feet), 30 must be used as the value for h in the above formula.

(2) The value used for p in the above formula must not be less than 27 dB less than the maximum ERP in any direction, or 0.1 Watt, whichever is more.

(3) The distance from the transmitting antenna to the service contour along any radial other than the eight cardinal radials is routinely calculated by linear interpolation of distance as a function of angle. However, in resolving petitions to deny, the FCC may calculate the distance to the service contour using the formula in paragraph (e) of this section with actual HAAT and ERP data for the inter-station radial and addition radials above and below the below the inter-station radial at 2.5° intervals.

(f) *UHF interfering contour.* For base and fixed stations transmitting on the UHF channels, the radial distance from

the transmitting antenna to the interfering contour along each cardinal radial is calculated as follows:

(1) If the radial antenna HAAT is less than 150 meters:

$$d = 9.471 \times h^{0.23} \times p^{0.15}$$

where:

d is the radial distance in kilometers
h is the radial antenna HAAT in meters
p is the radial ERP in Watts

Whenever the actual HAAT is less than 30 meters (98 feet), 30 must be used as the value for h in the above formula.

(2) If the radial antenna HAAT is 150 meters or more:

$$d = 6.336 \times h^{0.31} \times p^{0.15}$$

where:

d is the radial distance in kilometers
h is the radial antenna HAAT in meters
p is the radial ERP in Watts

(3) The value used for p in the above formula must not be less than 27 dB less than the maximum ERP in any direction, or 0.1 Watt, whichever is more.

(4) The distance from the transmitting antenna to the interfering contour along any radial other than the eight cardinal radials is routinely calculated by linear interpolation of distance as a function of angle. However, in resolving petitions to deny, the FCC may calculate the distance to the interfering contour using the appropriate formula in paragraph (f) of this section with actual HAAT and ERP data for the inter-station radial and additional radials above and below the inter-station radial at 2.5° intervals.

(g) *Protection for BETRS.* In applying the provisions of paragraph (a) of this section, if either or both of the transmitters involved is a BETRS central office station, the following contour substitutions must be used:

(1) The service contour of the BETRS central office station(s) is a circle, centered on the central office station antenna, with a radius of 40 kilometers (25 miles).

(2) The interfering contour of any station of any type, when determining whether it would overlap the service contour of a BETRS central office station, is calculated as follows:

$$d = 36.364 \times h^{0.2} \times p^{0.1}$$

§ 22.571

where:

d is the radial distance in kilometers

h is the radial antenna HAAT in meters

p is the radial ERP in Watts

Whenever the actual HAAT is less than 30 meters (98 feet), 30 must be used as the value for h in the above formula. The value used for p in the above formula must not be less than 27 dB less than the maximum ERP in any direction, or 0.1 Watt, whichever is more.

(h) *Assignment of mobile channels to base or fixed transmitters.* Mobile channels may be assigned to base or fixed transmitters if the following criteria are met:

(1) The paired base channel, as designated in § 22.561, is assigned to base transmitters in the same geographical area operated by the same licensee.

(2) The authorization is granted subject to the condition that no interference be caused to fixed receivers in use on or prior to the date of the grant.

§ 22.571 Responsibility for mobile stations.

Mobile stations that are subscribers in good standing to a two-way service in the Paging and Radiotelephone Service, when receiving service from that station, are considered to be operating under the authorization of that station. Licensees are responsible for exercising effective operational control over mobile stations receiving service through their stations. Mobile stations that are subscribers in good standing to a two-way service in the Paging and Radiotelephone Service, while receiving service from a different station, are considered to be operating under the authorization of such different station. The licensee of such different station is responsible, during such temporary period, for exercising effective operational control over such mobile stations as if they were subscribers to it.

§ 22.573 Use of base transmitters as repeaters.

As an additional function, base transmitters may be used as repeaters. Licensees must be able to turn the base transmitter on or off from the control point regardless of whether a subscriber-operated transmitter is transmitting.

47 CFR Ch. I (10–1–16 Edition)

§ 22.575 Use of mobile channel for remote control of station functions.

Carriers may remotely control station functions (e.g. shut down or reactivate base transmitters, turn aviation obstruction warning lights on or off, etc.) using a control transmitter operating on a mobile channel, subject to the conditions in this section and in § 22.567(h).

(a) The control transmitter must be capable of overriding transmissions from subscriber-operated transmitters if necessary. Subscriber-operated transmitters must not be capable of being used to deliberately or accidentally prevent the licensee from controlling the station.

(b) The licensee must implement measures designed to prevent station functions from being controlled by persons not authorized by the licensee to control the station.

(c) The control transmitter location must be within the composite service contour of the licensee's authorized station on the paired base channel.

§ 22.579 Operation of mobile transmitters across U.S.-Canada border.

Mobile stations licensed by Canada may receive two-way service while in the United States from stations licensed under this part, after authorization has been granted by the FCC. Mobile stations that normally operate under the authority of base stations licensed under this part may receive two-way service while in Canada from stations licensed under this part or by Canada, upon authorization by Canada.

§ 22.589 One-way or two-way application requirements.

In addition to information required by subparts B and D and § 22.529, applications for authorization to operate a paging transmitter on the channels listed in § 22.531, other than applications for a paging geographic area authorization, must contain the applicable supplementary information described in this section.

(a) *Interference exhibit.* Except as provided in paragraph (b) of this section, an exhibit demonstrating compliance with § 22.567 with regard to protected transmitters is required. This exhibit must: