

value of 1.0 should be used for the maximum radiation. The plot of the pattern should be oriented so that 0° corresponds to the maximum radiation of the directional antenna or, alternatively in the case of a symmetrical pattern, to the line of symmetry. The 0° on the plot should be referenced to the actual azimuth with respect to true North.

(3) A tabulation of the relative field pattern required in paragraph (c)(2), of this section. The tabulation should use the same zero degree reference as the plotted pattern, and be tabulated at least every 10°. In addition, tabulated values of all maximas and minimas, with their corresponding azimuths, should be submitted.

(4) All horizontal plane patterns must be plotted to the largest scale possible on unglazed letter-size polar coordinate paper (main engraving approximately 18 cm × 25 cm (7 inches × 10 inches)) using only scale divisions and subdivisions of 1, 2, 2.5 or 5 times 10<sup>nth</sup>. Values of field strength on any pattern less than 10% of the maximum field strength plotted on that pattern must be shown on an enlarged scale.

(5) The horizontal plane patterns that are required are the patterns for the complete directional antenna system. In the case of a composite antenna composed of two or more individual antennas, this means that the patterns for the composite antenna composed of two or more individual antennas, not the patterns for each of the individual antennas, must be submitted.

[30 FR 8847, July 14, 1965, as amended at 41 FR 28267, July 9, 1976; 47 FR 21500, May 18, 1982; 48 FR 21487, May 12, 1983; 52 FR 7423, Mar. 11, 1987; 52 FR 31404, Aug. 20, 1987; 58 FR 44951, Aug. 25, 1993; 62 FR 26722, May 14, 1997]

#### § 74.736 Emissions and bandwidth.

(a) The license of a low power TV, TV translator, or TV booster station authorizes the transmission of the visual signal by amplitude modulation (A5) and the accompanying aural signal by frequency modulation (F3).

(b) Standard width television channels will be assigned and the transmitting apparatus shall be operated so as to limit spurious emissions to the lowest practicable value. Any emissions

including intermodulation products and radio frequency harmonics which are not essential for the transmission of the desired picture and sound information shall be considered to be spurious emissions.

(c) Any emissions appearing on frequencies more than 3 MHz above or below the upper and lower edges, respectively, of the assigned channel shall be attenuated no less than:

(1) 30 dB for transmitters rated at no more than 1 watt power output.

(2) 50 dB for transmitters rated at more than 1 watt power output.

(3) 60 dB for transmitters rated at more than 100 watts power output.

(d) Greater attenuation than that specified in paragraph (c) of this section may be required if interference results from emissions outside the assigned channel.

[28 FR 13722, Dec. 14, 1963, as amended at 33 FR 8677, June 13, 1968; 36 FR 19592, Oct. 8, 1971; 47 FR 21500, May 18, 1982; 52 FR 31404, Aug. 20, 1987]

#### § 74.737 Antenna location.

(a) An applicant for a new low power TV, TV translator, or TV booster station or for a change in the facilities of an authorized station shall endeavor to select a site that will provide a line-of-sight transmission path to the entire area intended to be served and at which there is available a suitable signal from the primary station, if any, that will be retransmitted.

(b) The transmitting antenna should be placed above growing vegetation and trees lying in the direction of the area intended to be served, to minimize the possibility of signal absorption by foliage.

(c) A site within 8 kilometers of the area intended to be served is to be preferred if the conditions in paragraph (a) of this section can be met.

(d) Consideration should be given to the accessibility of the site at all seasons of the year and to the availability of facilities for the maintenance and operation of the transmitting equipment.

(e) The transmitting antenna should be located as near as is practical to the transmitter to avoid the use of long transmission lines and the associated power losses.