

## § 74.1250

## 47 CFR Ch. I (10–1–10 Edition)

possibility of signal absorption by foliage.

(b) Consideration should be given to accessibility of the site at all seasons of the year and to the availability of facilities for the maintenance and operation of the FM translator.

(c) Consideration should be given to the existence of strong radiofrequency fields from other transmitters at the translator site and the possibility that such fields may result in the retransmission of signals originating on frequencies other than that of the primary station.

(d) The transmitting antenna of an FM booster station shall be located within the protected contour of its primary station, subject to Note, § 74.1231 (h). The transmitting antenna of a commonly owned commercial FM translator station shall be located within the protected contour of its commercial primary FM station.

(e) A translator or booster station to be located on an AM antenna tower or located within 3.2 km of an AM antenna tower must comply with § 73.1692 of this chapter.

[35 FR 15388, Oct. 2, 1970, as amended at 55 FR 50698, Dec. 10, 1990; 58 FR 42026, Aug. 6, 1993; 62 FR 51063, Sept. 30, 1997]

### § 74.1250 Transmitters and associated equipment.

(a) FM translator and booster transmitting apparatus, and exciters employed to provide a locally generated and modulated input signal to translator and booster equipment, used by stations authorized under the provisions of this subpart must be certificated upon the request of any manufacturer of transmitters in accordance with this section and subpart J of part 2 of this chapter. In addition, FM translator and booster stations may use FM broadcast transmitting apparatus verified or approved under the provisions of part 73 of this chapter.

(b) Transmitting antennas, antennas used to receive signals to be rebroadcast, and transmission lines are not subject to the requirement for certification.

(c) The following requirements must be met before translator, booster or exciter equipment will be certificated in accordance with this section:

(1) Radio frequency harmonics and spurious emissions must conform with the specifications of § 74.1236 of this part.

(2) The local oscillator or oscillators, including those in an exciter employed to provide a locally generated and modulated input signal to a translator or booster, when subjected to variations in ambient temperature between minus 30 degrees and plus 50 degrees centigrade, and in primary supply voltage between 85 percent and 115 percent of the rated value, shall be sufficiently stable to maintain the output center frequency within plus or minus 0.005 percent of the operating frequency and to enable conformance with the specifications of § 74.1261 of this part.

(3) The apparatus shall contain automatic circuits to maintain the power output in conformance with § 74.1235(e) of this part. If provision is included for adjusting the power output, then the normal operating constants shall be specified for operation at both the rated power output and the minimum power output at which the apparatus is designed to operate. The apparatus shall be equipped with suitable meters or meter jacks so that the operating constants can be measured while the apparatus is in operation.

(4) Apparatus rated for transmitter power output of more than 1 watt shall be equipped with automatic circuits to place it in a nonradiating condition when no input signal is being received in conformance with § 74.1263(b) of this part and to transmit the call sign in conformance with § 74.1283(c)(2) of this part.

(5) For exciters, automatic means shall be provided for limiting the level of the audio frequency voltage applied to the modulator to ensure that a frequency swing in excess of 75 kHz will not occur under any condition of the modulation.

[55 FR 50698, Dec. 10, 1990, as amended at 63 FR 36606, July 7, 1998]

### § 74.1251 Technical and equipment modifications.

(a) No change, either mechanical or electrical, except as provided in part 2 of this chapter, may be made in FM translator or booster apparatus which