

they shall be located at the elevation where the current in the tower would be at a minimum if the tower were detuned in the horizontal plane, as determined by the moment method model parameters used to determine the antenna monitor parameters. Sample loops may be employed only when the towers are identical in cross-sectional structure, including both leg and cross member characteristics; if the towers are of unequal height, the sample loops shall be mounted identically with respect to tower cross members at the appropriate elevations above the base insulator. If the tower height used in the model is other than the physical height of the tower, the sampling loop shall be located at a height that is the same fraction of the total tower height as the minimum in tower current with the tower detuned in the model. Sample lines from the sensing element to the antenna monitor must be equal in both length (within one electrical degree) and characteristic impedance (within two ohms), as established by impedance measurements, including at the open-circuit resonant frequency closest to carrier frequency to establish length, at frequencies corresponding to odd multiples of $\frac{1}{4}$ wavelength immediately above and below the open circuit resonant frequency closest to carrier frequency, while open circuited, to establish characteristic impedance, and at carrier frequency or, if necessary, at nearby frequencies where the magnitude of the measured impedance is no greater than 200 ohms with the sampling devices connected. Samples may be obtained from current transformers at the output of the antenna coupling and matching equipment for base-fed towers whose actual electrical height is 120 degrees or less, or greater than 190 electrical degrees. Samples may be obtained from base voltage sampling devices at the output of the antenna coupling and matching equipment for base-fed towers whose actual electrical height is greater than 105 degrees. Samples obtained from sample loops located as described above can be used for any height of tower. For towers using base current or base voltage sampling derived at the output of the antenna coupling and matching equipment, the sampling de-

vices shall be disconnected and calibrated by measuring their outputs with a common reference signal (a current through them or a voltage across them, as appropriate) and the calibration must agree within the manufacturer's specifications. A complete description of the sampling system, including the results of the measurements described in this paragraph, shall be submitted with the application for license.

(ii) Proper adjustment of an antenna pattern shall be determined by correlation between the measured antenna monitor sample indications and the parameters calculated by the method of moments program, and by correlation between the measured matrix impedances for each tower and those calculated by the method of moments program. The antenna monitor sample indications must be initially adjusted to agree with the moment method model within ± 5 percent for the field ratio and ± 3 degrees in phase. The measured matrix impedances must agree with the moment method model within ± 2 ohms and ± 4 percent for resistance and reactance.

(3) Reference field strength measurement locations shall be established in directions of pattern minima and maxima. On each radial corresponding to a pattern minimum or maximum, there shall be at least three measurement locations. The field strength shall be measured at each reference location at the time of the proof of performance. The license application shall include the measured field strength values at each reference point, along with a description of each measurement location, including GPS coordinates and datum reference.

[36 FR 919, Jan. 20, 1971, as amended at 42 FR 36828, July 18, 1977; 49 FR 23348, June 6, 1984; 50 FR 32416, Aug. 12, 1985; 56 FR 64862, Dec. 12, 1991; 63 FR 33876, June 22, 1998; 66 FR 20756, Apr. 25, 2001; 73 FR 64561, Oct. 30, 2008]

§ 73.152 Modification of directional antenna data.

(a) If, after construction and final adjustment of a directional antenna, a measured inverse distance field in any direction exceeds the field shown on the standard radiation pattern for the pertinent mode of directional operation, an application shall be filed,

specifying a modified standard radiation pattern and/or such changes as may be required in operating parameters so that all measured effective fields will be contained within the modified standard radiation pattern. Permittees may also file an application specifying a modified standard radiation pattern, even when measured radiation has not exceeded the standard pattern, in order to allow additional tolerance for monitoring point limits.

(b) If, following a partial proof of performance, a licensee discovers that radiation exceeds the standard pattern on one or more radials because of circumstances beyond the licensee's control, a modified standard pattern may be requested. The licensee shall submit, concurrently, Forms 301-AM and 302-AM. Form 301-AM shall include an exhibit demonstrating that no interference would result from the augmentation. Form 302-AM shall include the results of the partial proof, along with full directional and nondirectional measurements on the radial(s) to be augmented, including close-in points and a determination of the inverse distance field in accordance with § 73.186.

(c) Normally, a modified standard pattern is not acceptable at the initial construction permit stage, before a proof-of-performance has been completed. However, in certain cases, where it can be shown that modification is necessary, a modified standard pattern will be acceptable at the initial construction permit stage. Following is a non-inclusive list of items to be considered in determining whether a modification is acceptable at the initial construction permit stage:

(1) When the proposed pattern is essentially the same as an existing pattern at the same antenna site. (e.g., A DA-D station proposing to become a DA-1 station.)

(2) Excessive reradiating structures, which should be shown on a plat of the antenna site and surrounding area.

(3) Other environmental factors; they should be fully described.

(4) Judgment and experience of the engineer preparing the engineering portion of the application. This must be supported with a full discussion of the pertinent factors.

(d) The following general principles shall govern the situations in paragraphs (a), (b), and (c) in this section:

(1) Where a measured field in any direction will exceed the authorized standard pattern, the license application may specify the level at which the input power to the antenna shall be limited to maintain the measured field at a value not in excess of that shown on the standard pattern, and shall specify the common point current corresponding to this power level. This value of common point current will be specified on the license for that station.

(2) Where any excessive field does not result in objectionable interference to another station, a modification of construction permit application may be submitted with a modified standard pattern encompassing all augmented fields. The modified standard pattern shall supersede the previously submitted standard radiation pattern for that station in the pertinent mode of directional operation. Following are the possible methods of creating a modified standard pattern:

(i) The modified pattern may be computed by making the entire pattern larger than the original pattern (*i.e.*, have a higher RMS value) if the measured fields systematically exceed the confines of the original pattern. The larger pattern shall be computed by using a larger multiplying constant, k , in the theoretical pattern equation (Eq. 1) in § 73.150(b)(1).

(ii) Where the measured field exceeds the pattern in discrete directions, but objectionable interference does not result, the pattern may be expanded over sectors including these directions. When this "augmentation" is desired, it shall be achieved by application of the following equation:

$$E(\phi, \theta)_{aug} = \sqrt{\{ E(\phi, \theta)_{std} \}^2 + A \{ g(\theta) \cos(180 D_A/S) \}^2}$$

where:

$E(\phi, \theta)_{std}$ is the standard pattern field at some particular azimuth and elevation angle, before augmentation, computed pursuant to Eq. 2, § 73.150(b)(1)(i).

$E(\phi, \theta)_{aug}$ is the field in the direction specified above, after augmentation.

$A = E(\phi, \theta)_{aug}^2 - E(\phi, \theta)_{std}^2$ in which ϕ is the central azimuth of augmentation. $E(\phi, \theta)_{aug}$

and $E(\phi, \theta)_{std}$ are the fields in the horizontal plane at the central azimuth of augmentation.

NOTE: “A” must be positive, except during the process of converting non-standard patterns to standard patterns pursuant to the *Report and Order in Docket No. 21473*, and in making minor changes to stations with patterns developed during the conversion. However, even when “A” is negative, “A” cannot be so negative that $E(\phi, \alpha)_{aug}$ is less than $E(\phi, \theta)_{th}$ at any azimuth or vertical elevation angle.

$g(\theta)$ is defined in § 73.150(b)(1)(i).

S is the angular range, or “span”, over which augmentation is applied. The span is centered on the central azimuth of augmentation. At the limits of the span, the augmented pattern merges into the un-augmented pattern. Spans may overlap.

D_A is the absolute horizontal angle between the azimuth at which the augmented pattern value is being computed and the central azimuth of augmentation. (D_A cannot exceed $1/2$ S.)

In the case where there are spans which overlap, the above formula shall be applied repeatedly, once for each augmentation, in ascending order of central azimuth of augmentation, beginning with zero degrees representing true North. Note that, when spans overlap, there will be, in effect, an augmentation of an augmentation. And, if the span of an earlier augmentation overlaps the central azimuth of a later augmentation, the value of “A” for the later augmentation will be different than the value of “A” without the overlap of the earlier span.

(iii) A combination of paragraphs (d)(2)(i) and (d)(2)(ii), of this section, with (d)(2)(i) being applied before (d)(2)(ii) is applied.

(iv) Where augmentation is allowable under the terms of this section, the requested amount of augmentation shall be centered upon the measured radial and shall not exceed the following:

(A) The actual measured inverse distance field value, where the radial does not involve a required monitoring point.

(B) 120% of the actual measured inverse field value, where the radial has a monitoring point required by the instrument of authorization.

Whereas some pattern smoothing can be accommodated, the extent of the requested span(s) shall be minimized and

in no case shall a requested augmentation span extend to a radial azimuth for which the analyzed measurement data does not show a need for augmentation.

(3) A Modified Standard Pattern shall be specifically labeled as such, and shall be plotted in accordance with the requirements of paragraph (b)(2) of § 73.150. The effective (RMS) field strength in the horizontal plane of $E(\phi, \alpha)_{std}$, $E(\phi, \alpha)_{th}$, and the root sum square (RSS) value of the inverse fields of the array elements (derived from the equation for $E(\phi, \alpha)_{th}$), shall be tabulated on the page on which the horizontal plane pattern is plotted. Where sector augmentation has been employed in designing the modified pattern, the direction of maximum augmentation (*i.e.*, the central azimuth of augmentation) shall be indicated on the horizontal plane pattern for each augmented sector, and the limits of each sector shall also be shown. Field values within an augmented sector, computed prior to augmentation, shall be depicted by a broken line.

(4) There shall be submitted, for each modified standard pattern, complete tabulations of final computed data used in plotting the pattern. In addition, for each augmented sector, the central azimuth of augmentation, span, and radiation at the central azimuth of augmentation ($E(\phi, \alpha)_{aug}$) shall be tabulated.

(5) The parameters used in computing the modified standard pattern shall be specified with realistic precision. Following is a list of the maximum acceptable precision:

(i) Central Azimuth of Augmentation: to the nearest 0.1 degree.

(ii) Span: to the nearest 0.1 degree.

(iii) Radiation at Central Azimuth of Augmentation: 4 significant figures.

(e) Sample calculations for a modified standard pattern follow. First, assume the existing standard pattern in § 73.150(c). Then, assume the following augmentation parameters:

Augmentation number	Central azimuth	Span	Radiation at central azimuth
1	110	40	1,300
2	240	50	52
3	250	10	130

Federal Communications Commission

§ 73.155

Following is a tabulation of part of the modified standard pattern:

Azimuth	0	30	60	Vertical angle
0	28.86	68.05	72.06
105	1,299.42	872.14	254.21
235	39.00	35.74	38.71
247	100.47	66.69	32.78

[46 FR 11992, Feb. 12, 1981, as amended at 56 FR 64862, Dec. 12, 1991; 66 FR 20756, Apr. 25, 2001]

§ 73.153 Field strength measurements in support of applications or evidence at hearings.

In the determination of interference, groundwave field strength measurements will take precedence over theoretical values, provided such measurements are properly taken and presented. When measurements of groundwave signal strength are presented, they shall be sufficiently complete in accordance with § 73.186 to determine the field strength at 1 mile in the pertinent directions for that station. The antenna resistance measurements required by § 73.186 need not be taken or submitted.

[44 FR 36037, June 20, 1979, as amended at 56 FR 64862, Dec. 12, 1991]

§ 73.154 AM directional antenna partial proof of performance measurements.

(a) A partial proof of performance consists of at least 8 field strength measurements made on each of the radials that includes a monitoring point. If the directional pattern has fewer than 4 monitored radials, the partial proof shall include measurements on those radials from the latest complete proof of performance which are adjacent to the monitored radials.

(b) The measurements are to be made within 3 to 15 kilometers from the center of the antenna array. When a monitoring point as designated on the station authorization lies on a particular radial, one of the measurements must be made at that point. One of the following methods shall be used for the partial proof:

(1) Measurement points shall be selected from the points measured in latest full proof of performance provided that the points can be identified with

reasonable certainty, and that land development or other factors have not significantly altered propagation characteristics since the last full proof. At each point, the licensee shall measure directional field strength for comparison to either the directional or the nondirectional field strength measured at that point in the last full proof.

(2) In the event that a meaningful comparison to full proof measurements cannot be made, the licensee shall measure both directional and nondirectional field strength at eight points on each radial. The points need not be limited to those measured in the last full proof of performance.

(c) The results of the measurements are to be analyzed as follows. Either the arithmetic average or the logarithmic average of the ratios of the field strength at each measurement point to the corresponding field strength in the most recent complete proof of performance shall be used to establish the inverse distance fields. (The logarithmic average for each radial is the antilogarithm of the mean of the logarithms of the ratios of field strength (new to old) for each measurement location along a given radial). When new nondirectional measurements are used as the reference, as described in paragraph (b)(2) of this section, either the arithmetic or logarithmic averages of directional to nondirectional field strength on each radial shall be used in conjunction with the measured nondirectional field from the last proof to establish the inverse distance field.

(d) The result of the most recent partial proof of performance measurements and analysis is to be retained in the station records available to the FCC upon request. Maps showing new measurement points, *i.e.*, points not measured in the last full proof, shall be associated with the partial proof in the station's records, and shall be provided to the FCC upon request.

[66 FR 20756, Apr. 25, 2001]

§ 73.155 Periodic directional antenna performance recertification.

A station licensed with a directional antenna pattern pursuant to a proof of performance using moment method