

## § 22.535

931.1375      931.3125      931.5125  
 931.1625      931.3375      931.5375  
 931.1875      931.3625      931.5625

(3) Longitudes other than specified in paragraphs (e)(1) and (e)(2) of this section:

931.0125      931.1625      931.2875      931.4125  
 931.0375      931.1875      931.3125      931.4625  
 931.0625      931.2125      931.3375      931.8625  
 931.1125      931.2375      931.3625  
 931.1375      931.2625      931.3875

(4) At any longitude, with authorization condition requiring coordinated, shared use and equal access by licensees in both countries:

931.4375      931.8875      931.9125      931.9375

(f) For the purpose of issuing paging geographic authorizations, the paging geographic areas used for UHF channels are the MEAs, and the paging geographic areas used for the low and high VHF channels are the EAs (see § 22.503(b)).

[59 FR 59507, Nov. 17, 1994, as amended at 59 FR 59954, Nov. 21, 1994; 62 FR 11635, Mar. 12, 1997; 63 FR 68945, Dec. 14, 1998; 64 FR 33784, June 24, 1999; 70 FR 19309, Apr. 13, 2005]

## § 22.535 Effective radiated power limits.

The effective radiated power (ERP) of transmitters operating on the channels listed in § 22.531 must not exceed the limits in this section.

(a) *Maximum ERP.* The ERP must not exceed the applicable limits in this paragraph under any circumstances.

Frequency range (MHz)	Maximum ERP (Watts)
35–36 .....	600
43–44 .....	500
152–159 .....	1400
931–932 .....	3500

(b) *Basic power limit.* Except as provided in paragraph (d) of this section, the ERP of transmitters on the VHF channels must not exceed 500 Watts.

(c) *Height-power limit.* Except as provided in paragraph (d) of this section, the ERP of transmitters on the VHF channels must not exceed the amount that would result in an average distance to the service contour of 32.2 kilometers (20 miles). The average distance to the service contour is calculated by taking the arithmetic mean of the distances determined using the

## 47 CFR Ch. I (10–1–15 Edition)

procedures specified in § 22.537 for the eight cardinal radial directions, excluding cardinal radial directions for which 90% or more of the distance so calculated is over water.

(d) *Encompassed interfering contour areas.* Transmitters are exempt from the basic power and height-power limits of this section if the area within their interfering contours is totally encompassed by the interfering contours of operating co-channel base transmitters controlled by the same licensee. For the purpose of this paragraph, operating transmitters are authorized transmitters that are providing service to subscribers.

(e) *Adjacent channel protection.* The ERP of transmitters must not exceed 500 Watts if they:

(1) Transmit on a channel in the 152–159 MHz frequency range and are located less than 5 kilometers (3.1 miles) from any station licensed in the Private Radio Services that receives on an adjacent channel; or,

(2) Transmit on channel 158.10 or 158.70 MHz and are located less than 5 kilometers (3.1 miles) from any station licensed in the Public Mobile Services that receives on either of the following adjacent channels: 158.07 MHz or 158.67 MHz.

(f) *Signal boosters.* The effective radiated power of signal boosters must not exceed 5 watts ERP under any normal operating condition.

[59 FR 59507, Nov. 17, 1994, as amended at 61 FR 31051, June 19, 1996]

## § 22.537 Technical channel assignment criteria.

The rules in this section establish technical assignment criteria for the channels listed in § 22.531. These criteria permit channel assignments to be made in a manner such that reception by public paging receivers of signals from base transmitters, within the service area of such base transmitters, is protected from interference caused by the operation of independent co-channel base transmitters.

(a) *Contour overlap.* The FCC may grant an application requesting assignment of a channel to a proposed base transmitter only if:

(1) The interfering contour of the proposed transmitter does not overlap